

CODEK

Wireless Pocket Scanner

SR5600

- professional scanner engine to decode bar code and QR code quickly, with its performance comparable to professional PDA device.
- Support finger wear and glove wear to provide a full range of industrial wearable solutions.
- Dual-mode Bluetooth to support BLE (Bluetooth Low Energy) and BR/EDR Bluetooth.
- Built-in 800mAh large-capacity removable lithium battery, with long battery life.
- Support multiple quick pairing modes, including Bluetooth list mode (default), scanning mode and NFC mode.
- A wide range of accessories available to support four-slot terminal charger, six-slot single-battery charger and multi-slot battery charger.



High-performance
laser scanning



Dual-mode
Bluetooth



800mAh large-
capacity battery



Quick pairing
mode



A wide range
of
accessories
available

Wireless Pocket Scanner/SR5600

Specifications

CODEK



CPU

1.2GHz



Dimensions

62.9×31×18.7mm



Material

Alloy, PC



Waterproof rate

IP65



Battery

Polymer lithium battery
3.8V / 800mAh/removable
Continuous working time 4h
Standby time more than 24h
Charging time less than 3h



Communication mode

Dual-mode Bluetooth
NFC quick pairing
ISO15693



Interface

Pogo pin *4



Notifications

Vibration
Buzzer
3-color LEDS



Buttons

Scan button×1
Power button×1



Scanning

2D/white light illumination laser aiming
Decoding Range: 5-40cm (based on actual scenarios)
Decoding speed: within 100ms



Storage capacity

Nor Flash 8MB



Environmental illumination

0-100000LUX



ESD

Air±15K
Contact±8K



Environmental parameters

Operating temperature: -20°C-50°C
5%-95%RH (Non-condensation)
Storage temperature: -30°C-70 5%-95%RH (Non-condensation)



Setting tools

Applet of WeChat
Local web page
Android App



Scanner lanyard



Ring-shaped support



Glove



Ring-shaped direct charger



Four-slot Terminal Charger



Six-slot Battery Charger